IMOU

Smart Outdoor Wi-Fi Security Kit

Quick Start Guide



Welcome

Thank you for choosing IMOU.

We are devoted to providing you easy smart home products. If you have problems using the product, please contact our service team at <code>service.global@imoulife.com</code> before returning your product.



Packing List



Recorder ×1 (1TB built-in HDD)

- Power Adapter
- Network Cable
- Mouse
- SATA Power Cable
- SATA Cable
- Rubber Feet Package
- Screw Package
- NVR QSG
- 1TB HDD (built-in)



Camera × 4

• Power Adapter





KIT QSG \times 1

- Waterproof Connector
- Screw Package
- Positioning Map

IPC QSG

Recorder






Power Input Port VGA Port Audio Input Port USB Port

LED Indicator Status	Recorder Status
HDD status indicator off	HDD is working properly
HDD status indicator on	HDD malfunction
Network status indicator off	Network connection is normal
Network status indicator on	Network connection failed
Power status indicator on	Power connection is normal

Camera





Press and hold the reset button for 10 s to reset the camera.

The pattern of the LED indicator is included in the following table.

LED Indicator Status	Device Status
Off	 Powered off/LED turned off Rebooting after reset
Red light on	Booting Device malfunction
Red light flashing	Network connection failed
Green light flashing	Waiting for network
Green light on	Operating properly
Green and red lights flashing alternately	Firmware updating

Connection

The recorder supports wireless connection.


Step 1 Put cameras next to the recorder and turn them on, and then turn on the Recorder.

The cameras will pair to the recorder automatically in 120 s.

Step 2 Initialize the recorder. For details, see "Local Basic Operation".

Step 3 Unplug the power cables of the cameras.


Step 4 Install cameras somewhere as needed.



The dotted line in the figure means that you can connect the recorder to a monitor through a VGA cable or HDMI cable. Choose one as needed.

Camera Installation

Make sure that the mounting surface is strong enough to hold at least three times of the device weight.



- **Step 1** Drill screw holes on the mounting surface as the positioning map shows, and then put in the expansion bolts.
- **Step 2** Attach the camera pedestal to the mounting surface with the self-tapping screws.
- Step 3 Power up the camera, and then adjust the lens to the ideal angle.

Local Basic Operation

1 Power On and Off

Startup:

Connect a monitor to the recorder, and then plug in the power to start the recorder

Shutdown:

Select Main Menu > SHUTDOWN to go to the SHUTDOWN interface, and then click Shut down. Unplug the recorder after the monitor is blank



♠ Do not force the recorder to shut down (or unplug the recorder) when the interface is indicating **Saving data** or the recorder is recordina videos.

2 Initialization

After turning on the recorder for the first time, you need to initialize the recorder by the following steps.

- 1) Set parameters for the administrator (the default username is admin).
- Draw an unlock pattern for login.
- Configure the password protection parameters.

Make sure that the email address for resetting password is correct.

3 Startup Wizard

For the first-time login, you can configure the recorder quickly by Startup Wizard, and set options such as general settings, Imou cloud, network settings and record settings.

4 Live View

After you logged in, the system goes to multiple-channel live view mode by default. You can view the live video of each channel.



5 Playback

Select **Main Menu > Playback** or right-click on the live interface and select **Search**.

You can play back records according to the configured record type, record time and channel.

App Operation

- **Step 1** Scan the QR code below to install Imou Life App. Register and then log in to Imou Life App.
 - Skip Step 1 if you have completed the download and registration of Imou Life App in the Startup Wizard.



Step 2 Tap + at the top-right corner of the **Device** tab, and then scan the QR code or enter the serial number of the Recorder to add it to the App.





Step 3 After adding the recorder to Imou, you can perform operations such as viewing video records, viewing alarms, setting alarm and sharing the recorder.







FAO

Q: Why does the recorder fail to start?

A: After the recorder is powered on, observe the power status indicator on the front panel. If the blue light is off, check the wiring. If the blue light is on and the recorder failed to start, contact the after-sales service.

Q: How to add a wireless IPC to a running recorder?

A: Put the wireless IPC next to the recorder and turn it on, Right-click the local GUI and select Wireless Pairing. After pairing completed, install the wireless IPC at a place as needed.

Q: Why are there no video records in local playback?

- A: Three possible reasons: 1. Wiring error. 2. HDD malfunction. 3. Record function is not enabled.
 Check method:
- Check the HDD status indicator. If the light is on , the HDD is working abnormally.
- Select STORAGE > HDD DETECT to run the diagnosis. Replace the HDD if there are damages.
- Right-click the local GUI and select Manual > Record to check if the record function is enabled.

Q: Why is the playback time inconsistent with actual time after enabling cloud storage?

A: Ensure that the IPC time is consistent with recorder time. Select SYSTEM > GENERAL > General to enable IPC Time Sync. You can also select SYSTEM > GENERAL > Date&Time to modify recorder time.