

SF-BNC4K-HDMI

SAFIRE



Features

- Safire
- BNC to HDMI Converter
- 1 BNC input
- 1 BNC output
- 1 HDMI 1080p output
- Input resolution up to 8 MP
- Input format TVI / CVI / AHD / CVBS
- 75 ohm and high impedance
- Possibility of loop between BNC

Specifications

Brand	Safire
Input	1 BNC input
Output	1 HDMI output / 1 BNC output
Loop between BNCs	Support
Input resolution	8 Mpx (HDTVI) / 8 Mpx (HDCVI) / 5 Mpx (AHD) / 1080p (CVBS)
Output resolution	HDMI 1080p
Audio	Does not have
Functions	Test of analog cameras up to 8 MP
Output Impedance	75 ohm / Hi-Z
Power	5VDC / 2 at max.
Working conditions	-25 ° ~ 75 °
Dimensions	20 (H) x 55.0 (W) x 66 (D) mm