

# SF-XVR8208A-HU

Safire Smart

XVR analog recorder 8 series

8CH HDTV/HDCVI/AHD/CVBS/ 8+8

IP

HDMI 4K and VGA / 2 HDD output

Maximum resolution 4K (6FPS)

Audio / Alarms



Safire Smart

XVR 5n1

8 CH video HDTV/HDCVI/AHD/CVBS / 8+8 IP

H.265/H.264

Resolution 4K (6FPS)

Alarms

Audio

Outputs 4K HDMI & VGA

Advanced motion detection on all channels

1CH with human and vehicle detection

Space for 2 HDD

Mouse

# Specifications

<b>Brand</b>	SAFIRE
<b>Video format</b>	HDTV / HDCVI / AHD / CVBS / IP
<b>Video inputs</b>	8 BNC channels (HDTV / HDCVI / AHD / CVBS)
<b>Hybrid configuration</b>	8 Channels from BNC (substitution) + 8 (extra) IP channels (up to 8 Mpx)
<b>Video outputs</b>	1 HDMI 4K, 1 VGA, 1 BNC
<b>Audio inputs</b>	8 RCA channels
<b>Audio outputs</b>	1 Channel RCA
<b>Bidirectional audio</b>	Reusing the audio input/output
<b>Video / audio compression</b>	H.265 / H.264
<b>Display resolution</b>	HDMI x 1 : 3840 x 2160 / 1920 x 1080 / 1280 x 1024 / 1024 x 768 VGA x 1 : 1920 x 1080 / 1280 x 1024 / 1024 x 768 BNC x 1 : CVBS
<b>BNC input resolution</b>	TVI/ AHD/CVI: 4K@15fps, 5MP@20fps, 4MP/3MP/1080P/720P/WD1@30fps
<b>Main Stream coding</b>	4K@6fps /7fps (PAL/NTSC) (only supported by the 1) channel 4K Lite@12fps/15fps (PAL/NTSC) 5MP@12fps (PAL / NTSC) 5MP Lite@20fps (PAL / NTSC) 4MP/3MP@12fps / 15fps (PAL / NTSC) 4MPLite/1080P/720P/WD1/D1 @25fps/ 30fps(PAL / NTSC)
<b>Simultaneous multifunction</b>	Pentaplex: Live, Recording, Playback, Backup and Remote Access
<b>Bit Rate</b>	32 Kbps – 5 Mbps
<b>Bandwidth</b>	16 Mbps (Incoming) / 40 Mbps (Outgoing)
<b>Alarms</b>	8 inputs / 2 relay
<b>Smart Features</b>	8CH Intelligent motion detection 1CH with detection of human and vehicle crossing line or intrusion in area
<b>Recording method</b>	Manual, scheduled, smart events
<b>Backup</b>	USB / Network
<b>Internal memory</b>	2 HDD SATA 3.5" of up to 10TB (not included)
<b>Communication</b>	1 x USB 3.0, 1 x USB 2.0 (Mouse and backup) / RJ45 (Ethernet) / 1 x e-SATA
<b>Remote access</b>	Web Browser, Safire Smartphone App and Safire Smart VMS software
<b>Power</b>	DC 12 V / 4 A (Consumption without HDD < 15 W)
<b>Dimensions / Weight</b>	45 (H) x 380 (W) x 268 (D) mm / 1.2 Kg